

# Terxon LX LCD Keypad

Art. no. AZ4210

Page 1 of 2



- For operating and programming the alarm panel
- Suitable for indoor and protected outdoor use
- Operate your alarm panel with PIN code or proximity key fob
- Proximity chip reader integrated

The Terxon LX LCD Keypad is an extension module for the Terxon LX. Installed near the entrance door, it allows you to quickly operate your alarm control panel. The LCD keypad is connected to the Terxon LX via a 5-wire bus cable. Up to 128 control units can be integrated into the alarm system. Arranged in various parts of your building, these extension modules provide additional convenience. The system can be conveniently activated or deactivated via any keypad using a PIN code and proximity chip key. The status of the alarm control panel is also displayed on the plain text display of the control unit. You can conveniently view and, of course, change system settings, programming and the 2000x event memory of the Terxon LX. The LCD keypad is designed in an elegant white color. Thus, it is not only an enhancement for each entrance area, but it is also optically in line with the wireless components of the Secvest 2WAY. Whenever you extend your alarm system, for example, with a wireless universal module or an 8-zone wireless extension, all wireless extension components of the Secvest 2WAY will match your existing system perfectly, not only from a technical standpoint, but also visually.

# Terxon LX LCD Keypad

Art. no. A74210

Page 2 of 2

## Technical Data:

Dimensions	(WxHxD) 134x134x23 mm
Connections	5-core bus, screw terminal for connection of two zones, loudspeaker
Display	Alphanumeric LCD display, 2 lines x 16 segments
Outputs	1 transistor switch output
Width	134 mm
Housing material	ABS
Height	134 mm
Length	23 mm
Power consumption	0,36 W
Max. operating temperature	55 °C
Max. humidity	94 %
Min. operating temperature	-10 °C
Installation location	Indoors and protected outdoor areas

Net weight	0,2 kg
Tamper monitoring	Yes
Switching outputs	1
IP protection class	54
Security level	2
DC voltage supply	12 V
Power consumption	30 mA
Environmental class	II
Certifications	INCERT, VSÖ, F&P, NCP
Zone closure	2 DEOL (FSL) if connected to bus (alarm panel)